

CONDUCTOR CLEANING BRUSH

INSTRUCTION MANUAL



USCC-010
1/8" - 3" Conductors



USCC-011
3" - 11" Conductors



USCC-010-PADS
USCC-011-PADS
Replacement Pad Set (3)

CLEANING MODES:

BACK & FORTH:



Push the Conductor Cleaning Brush over the conductor and allow the spring-loaded jaws to clean while using a back and forth motion.

CIRCULAR:



Push the Conductor Cleaning Brush over the conductor. Rotate around the conductor in both directions allowing the spring-loaded jaws to clean.

FLAT SURFACES:



The outside pad on the Conductor Cleaning Brush can scrub flat surfaces.

PAD REPLACEMENT:

STEP ONE:



Remove the old pad by removing one corner from the pad holder as shown.

STEP TWO:



Pull out the pad between the outer tabs.

STEP THREE:



Insert a new pad between the outer tabs as shown. Carefully bend the end so both corners can slide into the pad holder.